



Design LED 36 DMX Traits 7 Channels

Channel 1 - Rainbow:

0-7	No function
8-220	Rainbow colours
221-255	Crossfading colours from slow to fast

Channel 2 - Red:

0-255	Red (0-Black , 255-100% Red)
-------	--------------------------------

Channel 3 - Green:

0-255	Green (0-Black , 255- 100% Green)
-------	-------------------------------------

Channel 4 - Blue:

221-255	Blue (0-Black , 255- 100% Blue)
---------	-----------------------------------

Channel 5 - Strobe:

0-63	No function (shutter open)
64-95	Strobe effect slow to fast
96-127	No function (shutter open)
128-159	Pulse effect in sequences
160-191	No function (shutter open)
192-223	Random strobe effect slow to fast
224-255	No function (shutter open)

Channel 6 – reset, internal programs:

0-95	No function
96-111	Internal program 1
112-127	Internal program 2
128-143	Internal program 3
144-159	Internal program 4
160-175	Internal program 5
176-191	Internal program 6
192-207	Internal program 7
208-223	Internal program 8
224-255	No function

Channel 7 - General dimming (option 1)

0-5	blackout
6-255	dimming(2%-100%)